

PSU 19" AC/DC Linear Regulator, Single

Linear regulator for applications requiring very low output noise level.



CERTIFICATIONS



CARACTERISTICI

1 output voltage

High control accuracy, low residual ripple and low interference

Mains/line voltage 230 VAC (can be switched to 115 VAC with mains/line voltage conversion kit)

Suited for medical applications (8 mm safety clearances)

SPECIFICAȚII

Table 1/2

| Număr de catalog | Type | Input Voltage AC | Power | Number of Output Voltages | Voltage 1 | Current 1 |
|------------------|----------------------|------------------|-------|---------------------------|-----------|-----------|
| 13105-004 | 19" Linear Regulator | 230V | 16W | 1 | 24V | 0.6A |
| 13105-003 | 19" Linear Regulator | 230V | 15W | 1 | 15V | 1A |
| 13105-009 | 19" Linear Regulator | 230V | 36W | 1 | 24V | 1.5A |

| Număr de catalog | Type | Input Voltage AC | Power | Number of Output Voltages | Voltage 1 | Current 1 |
|------------------|----------------------|------------------|-------|---------------------------|-----------|-----------|
| 13105-001 | 19" Linear Regulator | 230V | 8W | 1 | 5V | 1.5A |
| 13105-011 | 19" Linear Regulator | 230V | 30W | 1 | 5V | 6A |
| 13105-008 | 19" Linear Regulator | 230V | 33W | 1 | 15V | 2.2A |
| 13105-007 | 19" Linear Regulator | 230V | 31W | 1 | 12V | 2.8A |
| 13105-012 | 19" Linear Regulator | 230V | 50W | 1 | 12V | 4.2A |
| 13105-014 | 19" Linear Regulator | 230V | 60W | 1 | 24V | 2.5A |
| 13105-006 | 19" Linear Regulator | 230V | 20W | 1 | 5V | 4A |
| 13105-002 | 19" Linear Regulator | 230V | 13W | 1 | 12V | 1.1A |
| 13105-013 | 19" Linear Regulator | 230V | 53W | 1 | 15V | 3.5A |

Table 2/2

| Număr de catalog | Rack Height | Rack Width | Depth | Package Quantity | Certifications |
|------------------|-------------|------------|----------|------------------|----------------------|
| 13105-004 | 3U | 6HP | 171.93mm | 1 | RoHS, CE, EN 62368-1 |
| 13105-003 | 3U | 6HP | 171.93mm | 1 | CE, EN 62368-1, RoHS |
| 13105-009 | 3U | 10HP | 171.93mm | 1 | CE, RoHS |
| 13105-001 | 3U | 6HP | 171.93mm | 1 | EN 62368-1, CE, RoHS |
| 13105-011 | 3U | 14HP | 171.93mm | 1 | CE, RoHS |
| 13105-008 | 3U | 10HP | 171.93mm | 1 | CE, RoHS |
| 13105-007 | 3U | 10HP | 171.93mm | 1 | CE, RoHS |
| 13105-012 | 3U | 14HP | 171.93mm | 1 | CE, RoHS |
| 13105-014 | 3U | 14HP | 171.93mm | 1 | RoHS, CE |
| 13105-006 | 3U | 10HP | 171.93mm | 1 | CE, RoHS |
| 13105-002 | 3U | 6HP | 171.93mm | 1 | CE, EN 62368-1, RoHS |
| 13105-013 | 3U | 14HP | 171.93mm | 1 | RoHS, CE |

DETALII SUPLIMENTARE DESPRE PRODUS

Please order Front Panel separately.

Output Data at Ta= 0 ... 50 °C.

AVERTIZARE

Produsele nVent trebuie instalate și utilizate numai așa cum este indicat în fișele de instrucțiuni și materialele de formare ale nVent. Fișele de instrucțiuni sunt disponibile pe www.nvent.com și de la reprezentantul dvs. de servicii clienți nVent. O instalare incorectă, o utilizare abuzivă, o aplicare greșită sau orice altă lipsă de respectare completă a instrucțiunilor și avertismentelor nVent poate duce la defectarea produsului, la deteriorarea proprietății, la răniri corporale grave și moarte și/sau poate anula garanția dvs.

North America

All locations
+1.763.422.2661
Chat with us:
nvent.com/schroff

Europe

Straubenhardt, Germany
+49.7082.794.0
Betschdorf, France
+33.3.88.90.64.90
Warsaw, Poland
+48.22.209.98.35
Assago, Italy
+39.02.932.7141
Chat with us:
nvent.com/schroff

Asia

Shanghai, China
+86.21.2412.6943
Qingdao, China
+86.532.8771.6101
Singapore
+65.6768.5800
Shin-Yokohama, Japan
+81.45.476.0271
Chat with us:
nvent.com/schroff

Middle East & India

Dubai, United Arab
Emirates
+971.4.378.1700
Bangalore, India
+91.80.6715.2001
Istanbul, Turkey
+90.216.250.7374
Chat with us:
nvent.com/schroff



Portofoliul nostru puternic de mărci:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE