

**DT**  , 240 kA, 120/240 V, 1Ph  
**3W+G**

## Data Solutions


???

### DTX240B120240SP



nVent ERICO DTX240 ??????? (SPD)  
 ??? IEC I ?? II ?? UL 1 ?? 2  
 ??? B ???DTX240 ???  
 240 kA ????????????????? C ???  
 (MCC)???????????? (HVAC) ?????nVent ERICO DTX240 ???  
 NEMA®-4X ???????????????

??



??

- ???????????????????? (UL)
- ????????????/??? SPD ???????????????
- ????????????????????????????????????
- RS-485 ????
- 10 ???

????

- ?????? (Un): 120/240 V
- ?????: 1Ph 3W+G
- ???????? (Uc): 150/300 VAC
- ?????? (In)?UL: 20kA 8/20 ?s
- ?????? (Imax)???: 240kA 8/20 ?s
- ???? (Imp)?????: 12.5kA 10/350 ?s

??: 50 – 60Hz

??????? (VPR)?L-G: 700V

??????? (VPR)?L-L: 1000V

??????? (VPR)?L-N: 600V

??????? (VPR)?N-G: 600V

????: L-N; L-PE; N-PE

????? (SCCR): 200kA

????? (In)?IEC: 40kA 8/20 ?s

????? (Up)?IEC: 1200 V @ 20 kA; 3000 V @ 100 kA

????? (Isc): 50kA

?: 240 to 80°C

????: ??? PC ?

?????: NEMA®-4X; UL® 50E 4 ?

????: 2.5 – 16mm<sup>2</sup>

?: 8 ?????

?????????: 2.0 A @ 240 V

????: ?C ??

????: ??????????; ??? LED; ???; OLED ???; ??/TOV ???????

?: ????????????

?????: CSA C22.2 ? 269.2 ?; UL® 1449 ? 5 ? 1/2 ??20 kA ??

?: ANSI®/IEEE® C62.41.2-2002 A ??B ?C ?; ANSI®/IEEE® C62.41.1-2002 A ??B ?C ?; ANSI®/IEEE® C62.45-2002 A ??B ?C ?; EN 61643-11 2 ?; IEC® 61643-11 II ?

?? (D): 98.3mm

?? (H): 330.7mm

?? (W): 222.5mm


????: 4.98kg

????: DT2180DTXM

??????

????????????DTX240FP ? DTX240SM

?



??

???? nVent ????????????????? nVent ??????? www.nvent.com ????????????? nVent ????????????????????????????????????? nVent  
??



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE