

# DT , 240 kA, 230/400 V, 3Ph+N TT

## Data Solutions

???

### DTX240B400TT



nVent ERICO DTX240 **SPD**  
 IEC I II UL 1 2  
 B DTX240  
 240 kA C  
 (MCC) (HVAC) nVent ERICO DTX240  
 NEMA®-4X

??

- ?? (UL)
- ?? SPD
- ??
- RS-485
- ?? 53 dB ??10 kHz ? 100 MHz?? F ??
- 10

???

- ?? (Un): 230/400 V
- ???: 3 ? 4W+G
- ?? (Uc): 300/520 VAC
- ?? (In)?IEC: 40kA 8/20 ?s
- ?? (In)?IEC?N-PE: 100kA 8/20 ?s
- ?? (Imax)?N-PE: 240kA 8/20 ?s
- ?? (Imax)?: 240kA 8/20 ?s
- ?? (Imp)?: 17.5kA 10/350 ?s
- ?? (Imp)?N-PE: 70kA 10/350 ?s
- ?: 50 – 60Hz
- ?: L-N; L-PE; N-PE

?: 240 to 80°C

?: ? Hoffman ???

????: ??

?????: NEMA®-4X; UL® 50E 4 ?; IP66

????: 2 – 13mm<sup>2</sup>

?????: 2.0 A @ 240 V

????: ?C ??

????? (Iscr): 50kA

????: ??????????; ??? LED?????????; ???; OLED ???; ???; ??/TOV ??????

?: ?????????????

????? (Up)?IEC: 1200 V @ 20 kA; 3000 V @ 100 kA

?: EN 61643-11 1 ?? ?; IEC® 61643-1 I ??H ?; ANSI®/IEEE® C62.41.2-2002 A ??B ?C ?; ANSI®/IEEE® C62.41.1-2002 A ??B ?C ?; ANSI®/IEEE® C62.45-2002 A ??B ?C ?

?? (D): 140.2mm


?? (H): 355.1mm

????: 9.75kg

?? (W): 329.9mm

????: DT1300M; SGT1100M

?



??

???? nVent ?????????????????? nVent ??????? www.nvent.com ?????????? nVent ??? nVent  
??



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE