



?? 1 (L1): 18000mm

?? 2 (L2): 100mm

????: ???

????: ???????

???: ?? GB/T 34016-2017 ? DIN EN 117 ????

?????: ??

?????: ?

?????: 500% min

?????: 2.5 – 3.5mm

?????: UL® 2885; IEC® 60754-1; IEC® 62821-2

?????: IK09

?????: UL® 2556; UL® 854

?????: IEC® 61034-2; ISO 5659-2; UL® 2885

?????: 20kV/mm

?????: UL® 94V-0

?????: 0.2mm

?????IEC: 1000V; 5000V

???????EN 50264-3-1: 6000V

?????: ?50 to 115°C

?: IEC® 60695-2-11???????? 960 °C?; IEC® 61439.1; IEC® 61439.1 II ?; IEC® 60364

?T 60 K: 1533A

?? 1 (W1): 108mm

?? 2 (W2): 100mm

?? [1] (H1): 28.2mm

?? [2] (H2): 14.8mm

??? (HS): 14mm

????: 66.96kg

A: 50mm

B: 50mm

C: 25mm

D: 25mm

2 ??????????: 1.46

2 ??????????: 2

?????: AS 3008; BS 7671; CEI 64-8; CSN; DIN VDE 0100; HD 384; IEC® 60364; NBR 5410; NEN 1010; NFC 15-100; NIBT-NIN; NP (2002); ÔNORM; REBT; RGIE-AREI

**??????**

????????????????????

| ??   | ?T 30°C | ?T 40°C | ?T 45°C | ?T 50°C | ?T 55°C | ?T 60°C | ?T 65°C | ?T 70°C |
|------|---------|---------|---------|---------|---------|---------|---------|---------|
| ???? | 0.71    | 0.82    | 0.87    | 0.91    | 0.96    | 1.00    | 1.04    | 1.08    |



??? nVent ?????????????????? nVent ??????? www.nvent.com ?????????????? nVent ?? nVent  
 ???



??????????:  
 CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE