

????

???: 561173

?: ??

?: Flexibar-2 ???

????????IEC: 800A

?: ?; ???

????????IEC: 240 mm²

????????IEC: 240 mm²

????? (ICW) 1 ? : 60kA

????????????IEC: 910A

???????nVent ERIFLEX Flexibar?IEC: 930A

???????UL/CSA: 760A

????? (Ipk): 52kA

???????? (ICC): 24.8kA

????? (SCCR): 100kA

???????IEC (Ui): 1000; 1500

???????UL (Vin): 1000

??????? : 1

????????????? : 240mm²

??? nVent ERIFLEX Flexibar ??: 2 x 20 x 1-8 x 32 x 1

??? DLO ??? : #2 - 262 kcmil

????????? : (2) 35 - 240 mm²

??????? : 2

??????? - ??: (2) 35 - 240 mm²

??????? : (2) #2 - 500 ????

?? (D): 103mm

?? (H): 191mm

?? (W): 54mm

????: 0.68kg

?????: UL® 1953

?: IEC® 60947-7-1

?????: IP 20

?????: UL® 94V-0

??????

SBF250?SB250SPCR?????UL1953????? ?UL® 1953?????????1250VAC/DC?

????????????????????7%

| □□□□□□□□□□ | | | | | | | | | | |
|-------------------------------|-----|-----|-----|------|------|------|------|------|------|------|
| ????*?? (°C) ????? 85°C ????? | | | | | | | | | | |
| ???? (°C) | 30° | 35° | 40° | 45° | 50° | 55° | 60° | 65° | 70° | 75° |
| ???? (d) | 1 | 1 | 1 | 0.94 | 0.88 | 0.82 | 0.75 | 0.67 | 0.58 | 0.47 |
| *???????????? | | | | | | | | | | |

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
 ???



?????????:
 CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE