

□□□□ , 80 A IEC, 85 A UL/CSA, □□
Line, 6 □□□ Load, □ , □□□□

Data Solutions

???

UD-80A



??



??

- ????????????????????????????????
- ??????????????
- ????????????????????
- ????????????????????
- ????? DIN ????????????????
- ??? 95%
- ????????????????????????????????(RoHS) ??
- ?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?
- ???
- ??????????????

????

???: 569010

??: ??

??????IEC: 80A

??????UL/CSA: 85A

?????: ??

?????: 6 ???

?: ?; ???

????????IEC: 16 mm²

????????IEC: 16 mm²

??????IEC (Ui): 1000

??????UL (Vin): 600

????? (ICW) 1 ? : 3kA

????? (Ipk): 22kA

???????? (ICC): 11kA

????? (SCCR): 100kA

????????: 1

?????????: 6-16 mm²

????????: 16 min

????????: 6

?????????: (2) 2,5 - 16 mm²; (4) 2,5 - 6 mm²

???????? - ??: (2) 2,5 - 16 mm²; (4) 2,5 - 6 mm²

????????: (2) #16 - #4; (4) #16 - #8

?????: IP 20

?? (D): 46mm

?? (H): 69mm

?? (W): 30mm

????: 0.07kg

?????: UL® 1059

?????: UL® 94V-0




?: IEC® 60947-7-1

??????

????????????160A?IEC????????????????

UL ?????????1000V AC/DC????????????

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*????????????										



??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/?????????????



??????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE