



, 250 A IEC, 255 A UL/CSA,
Line, 6 Load, ,

Data Solutions

???

UDF-250A



??



??

- ????????????????????????????????????
- ????????????
- ????????????????????
- ????????????????????
- ????? DIN ?????????????
- ??? 95%
- ????????????????????????????????(RoHS) ??
- ?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?
- ???
- ????????????

????

???: 569041

?: ??

??????IEC: 250A

??????UL/CSA: 255A

?????: ???

?????: 6 ???

?: ?; ???

????????IEC: 70 mm²

????????IEC: 16 mm²

??????IEC (Ui): 1000

??????UL (Vin): 600

????? (ICW) 1 ? : 9kA

????? (Ipk): 23kA

???????? (ICC): 11.5kA

????? (SCCR): 100kA

?????: 1

?????: 6

?????????: (6) 2,5 - 16 mm²

???????? - ??: (6) 2,5 - 16 mm²

?????: (6) #14 - #4

?????: IP 20

?? (D): 46mm

?? (H): 79mm

?? (W): 29mm

????: 0.15kg

?????: UL® 1059

?????: UL® 94V-0

?: IEC® 60947-7-1




??????

????????????160A?IEC????????????????

UL ?????????1000V AC/DC????????????

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*???????????										

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????? nVent
??



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE