

□□□□ , 160 A IEC, 200 A UL/CSA,
□□ Line, 7 □□ Load, □ , □□□□

Data Solutions

???

UDJ-160A



??



??

????????????????????????????????

????????????

????????????????????

????????????????????

????? DIN ?????????????

??? 95%

????????????????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

???

????????????

????

???: 569030

??: ??

??????IEC: 160A

??????UL/CSA: 200A

?????: ??

?????: 7 ???

?: ?; ???

????????IEC: 70 mm²

????????IEC: 16 mm²

??????IEC (Ui): 1000

??????UL (Vin): 600

????? (ICW) 1 ? : 11.8kA

????? (Ipk): 30kA

???????? (ICC): 15kA

????? (SCCR): 100kA

????????: 1

?????????: 10-70 mm²

????????: 8 min

????????: 7

?????????: (1) 6 - 16 ???; (6) 2,5 - 16 mm²

???????? - ??: (1) 6 - 16 ???; (4) 2,5 - 16 mm²

????????: (1) #14 - #2 ??? #14 - #10 ???; (6) #14 - #4

?????: IP 20

?? (D): 46mm

?? (H): 77mm

?? (W): 29mm

????: 0.15kg

?????: UL® 1059

?????: UL® 94V-0



?: IEC® 60947-7-1

??????

????????????160A?IEC????????????????

UL ?????????1000V AC/DC????????????

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*????????????										



??? nVent ?????????????????? nVent ??????? www.nvent.com ?????????????? nVent ?? nVent
??



??????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE