

MSP0 PDU, 0U, 30A(24A)NA/32A Int, 380-415V, 3P Wye, 6 CB, 36 Locking Combo

Data Solutions

???

EN6883



The Advantage Series Outlet Metered, Outlet Switched PDU family offers energy metering with advanced power and environmental monitoring options and remote outlet on/off switching. Comprehensive monitoring at the input phase, circuit breaker, and individual outlet levels offers advanced alerts of potential overloads. Billing-grade metering provides accurate power consumption data for energy use optimization. The hot-swappable network management controller features Gigabit and redundant ethernet communication with advanced support for external environmental sensors and rack security access solutions.

??

IEC 62368 listed. RoHS, and REACH compliant. See drawing for additional information.

UL 2900-1 certified for safety software cybersecurity for network-connectable products.

Dual network connectivity ports: 1x Gigabit Ethernet (10/100/1000 Mbps) and 1x (10/100 Mbps) connection/IP address

Ethernet cascading up to 64 PDUs

Each PDU can provide DC power sufficient to power network management electronics

Dual Ethernet ports for redundant network communications

Remote connectivity through HTTP(s), IPv4 and IPv6, SSH, Virtual Serial, SNMP (v1, v2c, v3), JSON-RPC, LDAP(S)

Data efficient REACT framework with native mobile device support

Tool-less hot swappable Network Management Card (NMC) with Cortex A-5 for microprocessing and memory that can be installed both upright and upside down for top or bottom power inputs

The border color of the NMC display is user programmable for power source identification by PDU

The NMC supports up to 10 digital sensors for environmental and/or electronic lock monitoring

Display languages include English, Spanish, German, French, Italian, Korean, Japanese, and Chinese (simplified)

????

????: Enlogic

?: ? PDU

????: ??

????: (18) ?? C13/C15; (18) ?? C13/C15/C19/C21

????: 36

?: ??

????: ?

????: 17.3 kVA ??; 22.1 kVA ??

????: 3000mm

?: 20 A?1 ??Hy-MagA

?????: 6

????: 415V

?????: 230VAC

?????: 36

?????????: 30 A (24 A) ??; 32 A ??

????: 0U

??/??: ?

????: 208 – 230VAC

????: ??

????: ??? IEC60309 530/532P6 (IP44)

?????????: ?

?: ?

?: ????

?: 1720mm

?: 56mm

?: 75mm

????: 1

?????: 3m

??????

Warranty : nVent Enlogic branded equipment provided shall be free from manufacturing defects for a period of five (5) years from the invoice date to the original purchaser.

??

???? nVent ?????????????????? nVent ??????? www.nvent.com ??????????? nVent ??? nVent ???/??????????????



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE