

??: -29 dB @ 100 kHz

??: 50 – 60Hz

??????? (VPR)?L-G: 1800V

??????? (VPR)?L-L: 1800V

????: L-PE

????? (SCCR): 200kA

????? (In)?IEC: 40kA 8/20 ?s

????? (In)?UL: 20kA 8/20 ?s

????? (Up)?IEC: 1200 V @ 20 kA; 3000 V @ 100 kA

????? (Isc): 50kA

?: 240 to 80°C

????: ??? PC ?

?????: NEMA®-4X; UL® 50E 4 ?

????: 2.5 – 16mm²

?: 4 ?????

?????????: 2.0 A @ 240 V

????: ?C ?

????: ??????????; ??? LED; ???; OLED ???; ??/TOV ???????

?: ????????????

?????: CSA C22.2 ? 269.2 ?; UL® 1283 ? 7 ?; UL® 1449 ? 5 ? 2 ?20 kA ??

?: ANSI®/IEEE® C62.41.1-2002 A ??B ?C ?; ANSI®/IEEE® C62.41.2-2002 A ??B ?C ?; ANSI®/IEEE® C62.45-2002 A ??B ?C ?; EN 61643-11 2 ?; IEC® 61643-11 II ?

?? (D): 98.3mm

?? (H): 330.7mm

?? (W): 101.6mm


????: 2.88kg

????: DT2510DTXM

??????

????????????DTX120FP ? DTX120SM

?



??

???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ????????????????????????????????????? nVent
??



??????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE