

DT , **240 kA, 230/400 V,**
3Ph+N TT

Data Solutions

???

DTX240B400TT



nVent ERICO DTX240 ??????? (SPD)
 ??? IEC I ?? II ?? UL 1 ?? 2
 ??? B ????DTX240 ???
 240 kA ????????????? C ?????????????????????????????????
 (MCC)???????????? (HVC) ?????nVent ERICO DTX240 ???
 NEMA®-4X ?????????????

??

???????????? (UL)

??????/??? SPD ????????????

????????????????

RS-485 ???? ?

?? 53 dB ???10 kHz ? 100 MHz???? F ??

10 ???

????

?????? (Un): 230/400 V

????: 3 ? 4W+G

???????? (Uc): 300/520 VAC

?????? (In)?IEC: 40kA 8/20 ?s

????? (In)?IEC?N-PE: 100kA 8/20 ?s

????? (Imax)?N-PE: 240kA 8/20 ?s

????? (Imax)???: 240kA 8/20 ?s

???? (Iimp)?????: 17.5kA 10/350 ?s

???? (Iimp)?N-PE: 70kA 10/350 ?s

??: 50 – 60Hz

????: L-N; L-PE; N-PE

??: 240 to 80°C

?: ? Hoffman ?

?: ?

?: NEMA®-4X; UL® 50E 4 ?; IP66

?: 2 – 13mm²

?: 2.0 A @ 240 V

?: ?C ?

?: (Iscrr): 50kA

?: ???? LED?????; ??: OLED ?; ??: ?/TOV ?????

?: ?????

?: (Up)?IEC: 1200 V @ 20 kA; 3000 V @ 100 kA

?: EN 61643-11 1 ? ?; IEC® 61643-1 I ?II ?; ANSI®/IEEE® C62.41.2-2002 A ?B ?C ?; ANSI®/IEEE® C62.41.1-2002 A ?B ?C ?; ANSI®/IEEE® C62.45-2002 A ?B ?C ?

?(D): 140.2mm


?(H): 355.1mm

?: 9.75kg

?(W): 329.9mm

?: DT1300M; SGT1100M

?



??

???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE