


Flexbus 220 mm² 15,000 mm x 25 mm x 12.5 mm x 19.2 kg

Data Solutions

???

FLEXCORE220L15



nVent ERIFLEX Flexbus
??
????????????????????????????????Flexbus
??Flexbus
???????????????? (LSHFFR) ????? II
???????????????????????????? 2-25 ????????????????? 500A ?
6300A ????????? 1600kVA ?????????????????????????
3150kVA ?????????????

??



??

????????????????
????????????????
????????
????????
????????????????????????????
???? 400kVA (560 A) ? 1600kVA (2250 A) ????????????????????? 2000kVA (2800 A) ? 3150kVA (4435 A) ?????????????
Flexbus ?????????????????

????

??? : 508413
??? : 220mm ²

?? 1 (L1): 15000mm

?? 2 (L2): 50mm

????: ???

????: ???????

???: ?? GB/T 34016-2017 ? DIN EN 117 ???

?????: ??

?????: ?

?????: 500% min

????: 2.5 – 3.5mm

?????: UL® 2885; IEC® 60754-1; IEC® 62821-2

?????: IK09

?????: UL® 2556; UL® 854

?????: IEC® 61034-2; ISO 5659-2; UL® 2885

????: 20kV/mm

?????: UL® 94V-0

????: 0.2mm

????IEC: 1000V; 5000V

??????EN 50264-3-1: 6000V

????: ?50 to 115°C

?: IEC® 60695-2-11??????? 960 °C?; IEC® 61439.1; IEC® 61439.1 II ?; IEC® 60364

?T 60 K: 666A

?? 1 (W1): 58mm

?? 2 (W2): 50mm

?? [1] (H1): 16.2mm

?? [2] (H2): 9mm

??? (HS): 11mm

????: 18.9kg

A: 25mm

C: 25mm

D: 12.5mm

2 ??????????: 1.56


2 ??????????: 2

????: AS 3008; BS 7671; CEI 64-8; CSN; DIN VDE 0100; HD 384; IEC® 60364; NBR 5410; NEN 1010; NFC 15-100; NIBT-NIN; NP (2002); ÔNORM; REBT; RGIE-AREI

??????

????????????????

□□□□□□□□								
??	?T 30°C	?T 40°C	?T 45°C	?T 50°C	?T 55°C	?T 60°C	?T 65°C	?T 70°C
????	0.71	0.82	0.87	0.91	0.96	1.00	1.04	1.08



???? nVent ?????????????????? nVent ??????? www.nvent.com ???????????? nVent ?????????????????????????????????????? nVent
??/??????????????



?????????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE