

IBSHY 830 mm

Data Solutions

???

IBSHY32-830



IBSHY ????????? 125/160
 ???IBSHY
 ???IBSHY
 ??????????????????? 32 ????? (63.15 kcmil)??? 230 ??? 830 ???9.1
 ??? 32.7 ???
 ??? ISO 9001 2015
 ???IBS
 HY ?????????????????????????????????????
 IBSHY
 ???
 ?????????????????????
 ???
 ?????????????????????????????????????IBSHY ?????
 125/160 ????????????????????????????????? nVent
 ERIFLEX ???

??



??

??? 125/160 ?????????????????????

????????????????

????????????

???????

????????????

????????????

????????????????

?? NF EN 45545???? R22 ? R23 ?? HL3 ?

DNV GL® ?????????

????????

????????????????????(RoHS) ??

????


???: 558595
?????????: 160A
?: ??
?: ?; ??????????
?????: UL® 1441 VW-1
???????IEC (Ui): 1000; 1500
?????? (Ipk): 15kA
?????: 0.15mm
?????: ?60 to 250°C
?: IEC® 60439.1; IEC® 61439.1
?????: 32mm²
?? (L): 830mm
A: 11mm
B: 25mm
C: 3mm
D: 5mm
??? 1 (HS1): 6.5mm
??? 2 (HS2): 10.5mm
?????: 0.24kg

??????

?T = ???? – ???????

??

□□□□□	
□□□□□□	125/160 A
□□□□	IBSHY32x
Schneider Electric® Compact® (IEC)	NSA NG 125
Square D® PowerPact® (UL)	H ??
ABB® Tmax® (IEC)	T1 T2 XT1 XT2
ABB® Tmax® (UL)	T1 T2 XT1 XT2
GE® Record Plus® (IEC/UL)	FD 160
Siemens® Sentron® (IEC/UL)	VL160X 3VL1 VL160 3VL2
Moeller® xEnergy® (IEC)	NZM1
Cutler Hammer® G ?? (UL)	EG ??
Legrand® (IEC)	DPX 160 DPX3 160
Hager® (IEC)	h3 160
Rockwell/Allen Bradley (UL)	G ?? H ??
OEZ (IEC)	BC160N



???? nVent ????????????????? nVent ??????? www.nvent.com ????????????? nVent ????????????????????????????????????? nVent
??/????????????



??????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE