


□□□ , □□ -□□ , 230 A IEC, □ , □□□□□

Data Solutions

???

SB160AL



nVent ERIFLEX
????????????????????(???????)??/?????? DIN
????/?????????????????????????????????????
????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ?????

??



??

????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????

????????????????

????????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????????

????????

??? 95%

????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

????????? ??????

????

- ???: 561162
- ?: ??
- ?: ??-??
- ????????IEC: 230A
- ?: ?; ???
- ????????IEC: 70 mm²
- ????????IEC: 70 mm²
- ????? (ICW) 1 ? : 14.4kA
- ????????IEC: 230A
- ????????UL/CSA: 200A
- ????? (Ipk): 42kA
- ???????? (ICC): 20kA
- ????? (SCCR): 100kA
- ????????IEC (Ui): 1000; 1500
- ????????UL (Vin): 1000
- ????????: 1
- ?????????: 35-70 mm²; #2 - 3/0
- ?????????: 35-70 mm²; #2 - 3/0
- ????????: 1
- ???????? - ??: 35-70 mm²
- ?? (D): 55mm
- ?? (H): 111mm
- ?? (W): 27.7mm
- ????: 0.1kg
- ?????: UL® 1059
- ?: IEC® 60947-7-1
- ?????: IP 20
- ?????: UL® 94V-0

??????

SBF250?SB250SPCR?????UL1953????? ??UL® 1953????????1250VAC/DC?

????????????????????7%

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*???????????										

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????? nVent
 ???



?????????:
 CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE