

□□□ , □□ -□□ , 400 A IEC, □ ,
□□□□□

Data Solutions

???

SB250



nVent ERIFLEX
????????????????????(???????)??/?????? DIN
?????/????????????????????????????????????
????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ?????

??



??

- ???????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????
- ?????????????????
- ????????????????????????????????????
- ???????????????
- ???????????????????????
- ???????????????????????
- ????? DIN ????????????????
- ???????????????
- ?? 95%
- ????????????????????????????(RoHS) ??
- ?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?
- ???????????? ????????

????

???: 561159

?: ??

?: ??-??

????????IEC: 400A

?: ?; ???

????????IEC: 120 mm²

????????IEC: 120 mm²

????? (ICW) 1 ? : 14.4kA

????????IEC: 400A

????????UL: 255A

????? (Ipk): 42kA

???????? (ICC): 20kA

????? (SCCR): 100kA

????????IEC (Ui): 1000; 1500

????????UL (Vin): 1250

????????: 1

?????????: 35 - 120 mm²; #6 - 250 ????

?????????: 35 - 120 mm²; #6 - 250 ????

????????: 1

???????? - ??: 35 - 120 mm²

?? (D): 58mm

?? (H): 111mm

?? (W): 31.5mm

????: 0.3kg

?????: UL® 1059

?: IEC® 60947-7-1

?????: IP 20

?????: UL® 94V-0

??????

SBF250?SB250SPCR?????UL1953????? ??UL® 1953????????1250VAC/DC?

????????????????????7%

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*???????????										

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
 ???



?????????:
 CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE