


□□□ , □□ -□□ , 500 A IEC, □ ,
□□□□□

Data Solutions

???

SB400AL



nVent ERIFLEX

????????????????????(???????)??/?????? DIN
????/?????????????????????????????????

????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ?????

??



??

??????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ?????

????????????????

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????

????????

??? 95%

????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

????????? ??????

???: 561164
?: ??
?: ??-??
????????IEC: 500A
?: ?; ???
????????IEC: 240 mm²
????????IEC: 240 mm²
????? (ICW) 1 ? : 28.8kA
???????IEC: 610A
???????UL/CSA: 335A
????? (Ipk): 51kA
???????? (ICC): 24.3kA
????? (SCCR): 100kA
???????IEC (Ui): 1000; 1500
???????UL (Vin): 1250
????????: 1
?????????: 95 - 240 mm²; 3/0 - 400 kcmil
?????????: 95 - 240 mm²; 3/0 - 400 kcmil
????????: 1
???????? - ??: 95 - 240 mm²
?? (D): 82mm
?? (H): 146.4mm
?? (W): 41.5mm
????: 0.25kg
?????: UL® 1059
?: IEC® 60947-7-1
?????: IP 20
?????: UL® 94V-0

SBF250?SB250SPCR?????UL1953????? ??UL® 1953??????????1250VAC/DC?

????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*?????????????										



???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/?????????????



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE