

PDU EN2350 230VAC 1-PH 32 A

Data Solutions

???

EN2350



Modular, compact intelligent PDU with inlet metering. Ultra-Low Profile Design

??

Enlogic EN2xxx PDU

???

???

???

?? (10/100)

iPDU 64 PDU

???

?? 230 VAC 1 ?

C13/C19 ?

???

???: Enlogic

?: ? PDU

???: ?

???: (20) C13/C15; (20) C13/C15/C19/C21

???: 40

??: ??

???: 20 A?1 ??Hy-Mag

????: ?

?????: 2

????: 7.4 kVA

?????: 3m

?????: ????

????: 200 – 240V

?: 1 ?

?????: 7.44 kVA

????: 230V

??/??: ?

????: 230VAC

?????: 32 A

????: IEC 60309 332P6 (IP44)

????: 0U

?????: ?

????: ??

?: ?

?: ????

?: 1490mm

?: 56mm

?: 75mm

?: 9.12kg

????: 1

?????: 5kAIC

??????

????????????

??

???? nVent ????????????????? nVent ??????? www.nvent.com ????????????? nVent ????????????????????????????????? nVent
??/????????????



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE