

# PSU 19" AC/DC Linear Regulator, Single

Linear regulator for applications requiring very low output noise level.



## CERTIFICATIONS



## VLASTNOSTI

1 output voltage

High control accuracy, low residual ripple and low interference

Mains/line voltage 230 VAC (can be switched to 115 VAC with mains/line voltage conversion kit)

Suited for medical applications (8 mm safety clearances)

## SPECIFIKACE

Table 1/2

Katalogové číslo	Typ	Vstupní napětí AC	Power	Number of Output Voltages	Voltage 1	Current 1
13105-004	19" Linear Regulator	230V	16W	1	24V	0.6A
13105-003	19" Linear Regulator	230V	15W	1	15V	1A
13105-009	19" Linear Regulator	230V	36W	1	24V	1.5A

Katalogové číslo	Typ	Vstupní napětí AC	Power	Number of Output Voltages	Voltage 1	Current 1
13105-001	19" Linear Regulator	230V	8W	1	5V	1.5A
13105-011	19" Linear Regulator	230V	30W	1	5V	6A
13105-008	19" Linear Regulator	230V	33W	1	15V	2.2A
13105-007	19" Linear Regulator	230V	31W	1	12V	2.8A
13105-012	19" Linear Regulator	230V	50W	1	12V	4.2A
13105-014	19" Linear Regulator	230V	60W	1	24V	2.5A
13105-006	19" Linear Regulator	230V	20W	1	5V	4A
13105-002	19" Linear Regulator	230V	13W	1	12V	1.1A
13105-013	19" Linear Regulator	230V	53W	1	15V	3.5A

Table 2/2

Katalogové číslo	Rack Height	Rack Width	Hloubka	Množství v balení	Certifications
13105-004	3U	6HP	171.93mm	1	RoHS, CE, EN 62368-1
13105-003	3U	6HP	171.93mm	1	CE, EN 62368-1, RoHS
13105-009	3U	10HP	171.93mm	1	CE, RoHS
13105-001	3U	6HP	171.93mm	1	EN 62368-1, CE, RoHS
13105-011	3U	14HP	171.93mm	1	CE, RoHS
13105-008	3U	10HP	171.93mm	1	CE, RoHS
13105-007	3U	10HP	171.93mm	1	CE, RoHS
13105-012	3U	14HP	171.93mm	1	CE, RoHS
13105-014	3U	14HP	171.93mm	1	RoHS, CE
13105-006	3U	10HP	171.93mm	1	CE, RoHS
13105-002	3U	6HP	171.93mm	1	CE, EN 62368-1, RoHS
13105-013	3U	14HP	171.93mm	1	RoHS, CE

## DALŠÍ PODROBNOSTI O PRODUKTU

---

Please order Front Panel separately.

Output Data at Ta= 0 ... 50 °C.

## UPOZORNĚNÍ

---

Produkty nVent musí být instalovány a používány pouze tak, jak je uvedeno v instrukčních listech a materiálech pro školení nVent. Instrukční listy jsou k dispozici na [www.nvent.com](http://www.nvent.com) a od vašeho zástupce zákaznického servisu nVent. Nesprávná instalace, zneužití, nesprávné použití nebo jiný nedostatek úplného dodržování pokynů a varování nVent může způsobit selhání produktu, poškození majetku, vážné zranění osob a smrt a/nebo zrušit vaši záruku.

### North America

All locations  
+1.763.422.2661  
Chat with us:  
[nvent.com/schroff](http://nvent.com/schroff)

### Europe

Straubenhardt, Germany  
+49.7082.794.0  
Betschdorf, France  
+33.3.88.90.64.90  
Warsaw, Poland  
+48.22.209.98.35  
Assago, Italy  
+39.02.932.7141  
Chat with us:  
[nvent.com/schroff](http://nvent.com/schroff)

### Asia

Shanghai, China  
+86.21.2412.6943  
Qingdao, China  
+86.532.8771.6101  
Singapore  
+65.6768.5800  
Shin-Yokohama, Japan  
+81.45.476.0271  
Chat with us:  
[nvent.com/schroff](http://nvent.com/schroff)

### Middle East & India

Dubai, United Arab  
Emirates  
+971.4.378.1700  
Bangalore, India  
+91.80.6715.2001  
Istanbul, Turkey  
+90.216.250.7374  
Chat with us:  
[nvent.com/schroff](http://nvent.com/schroff)



Naše portfolio silných značek:

**CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE**